

## IN THE CLAIMS

Please amend the claims as follows:

What is claimed is:

1. (previously presented) A transmitter apparatus comprising:
  - an encoder and modulator that generates an encoded and modulated transmit signal from an input signal;
  - a digital to analog converter, coupled to the encoder and modulator, for generating an analog representation signal of the encoded and modulated transmit signal;
  - an effectively continuously valued mapping function that selects an output value for a power amplifier control signal in response to a combination of a peak to average power ratio signal and a desired average transmit power signal, the effectively continuously valued mapping function comprising a table having a plurality of output values for the power amplifier control signals each with a corresponding desired transmit power value; and
  - a power amplifier coupled to the analog representation signal and the power amplifier control signal, at least one parameter within the power amplifier being adjusted in response to the power amplifier control signal.
2. (canceled)
3. (canceled)
4. (canceled)
5. (original) The apparatus of claim 1 wherein the power amplifier control signal is an analog signal.
6. (original) The apparatus of claim 1 wherein the power amplifier control signal is a digital signal.
7. (previously presented) The apparatus of claim 1 wherein the mapping function selects the

output values within the function with corresponding transmit power values for an optimized transmitter power efficiency while still meeting out of band spurious emissions and waveform quality requirement.

8. (previously presented) The apparatus of claim 1 wherein the at least one parameter within the power amplifier is at least one of a bias, a power supply voltage, a stage switch-in, a stage switch-out, a turning on, a turning off, a gain, a gain distribution, a conducting angle, an amplifier class change, a load, or an impedance.

9. (original) The apparatus of claim 1 wherein the at least one parameter is any transmitter apparatus parameter that affects transmitter efficiency.

10. (currently amended) The apparatus of claim 1 wherein the combination of a peak to average power ratio signal and a desired average transmit power signal~~desired-transmit-power signal~~ is converted to an analog signal prior to being input to the mapping function.

11. (previously presented) A transmitter apparatus in a wireless mobile device, the apparatus comprising:

- an encoder and modulator that generates an encoded and modulated transmit signal from an input signal, and generates a data indicator signal corresponding to the type of encoded and modulated transmit signal;

- a digital to analog converter, coupled to the encoder and modulator, for generating an analog representation signal of the encoded and modulated transmit signal;

- a first mapping function, coupled to the encoder and modulator, that generates a peak to average power ratio signal in response to the data indicator signal;

- a summer that generates a peak transmit power signal by summing the peak to average power ratio signal and a desired average transmit power signal;

- a second mapping function that generates an effectively continuously valued power amplifier control signal in response to the peak transmit power signal, the second mapping function comprising a table having a plurality of power amplifier control signal values each corresponding to a peak transmit power value for an optimized transmitter power efficiency while still meeting out of band spurious emissions and waveform quality requirement

an automatic gain control amplifier, coupled to the digital to analog converter, for generating an amplified analog representation signal in response to the desired average transmit power signal; and

a power amplifier with an input port coupled to the amplified analog representation signal and a control port coupled to the power amplifier control signal, at least one parameter of the power amplifier being adjusted in response to the power amplifier control signal.

12. (original) The apparatus of claim 11 wherein the first mapping function comprises a table of a plurality of peak to average power ratio values each having a corresponding data indicator.

13. (original) The apparatus of claim 11 and further including a digital to analog converter coupled between the second mapping function and the power amplifier such that the power amplifier control signal is converted to an analog representation of the power amplifier control signal.

14. (original) The apparatus of claim 11 wherein the power amplifier control signal is an analog signal that is low pass filtered prior to the power amplifier.

15. (original) The apparatus of claim 11 wherein the peak transmit power signal is converted to an analog signal prior to being input to the second mapping function.

16. (previously presented) A transmitter apparatus in a wireless mobile device, the apparatus comprising:

an encoder and modulator that generates an encoded and modulated transmit signal from an input signal, and generates a data indicator signal corresponding to the type of encoded and modulated transmit signal;

a digital to analog converter, coupled to the encoder and modulator, for generating an analog representation signal of the encoded and modulated transmit signal;

a first mapping function, coupled to the encoder and modulator, that generates a peak to average power ratio signal in response to the data indicator signal;

a desired power indicator generator that generates a desired average transmit power signal in response to an open loop power control signal and a closed loop power control signal;

a summer that generates a peak transmit power signal by summing the peak to average power ratio signal and the desired average transmit power signal;

a second mapping function that generates an effectively continuously valued power amplifier control signal in response to the peak transmit power signal, the second mapping function comprising a table having a plurality of power amplifier control signal values each corresponding to a peak transmit power value for an optimized transmitter power efficiency while still meeting out of band spurious emissions and waveform quality requirement

an automatic gain control amplifier, coupled to the digital to analog converter, for generating an amplified analog representation signal in response to the desired average transmit power signal; and

a power amplifier with an input port coupled to the amplified analog representation signal and a control port coupled to the power amplifier control signal, at least one parameter of the power amplifier being adjusted in response to the power amplifier control signal.

17. (currently amended) A transmitter apparatus comprising:

an encoder and modulator that generates an encoded and modulated transmit signal from an input signal;

a digital to analog converter, coupled to the encoder and modulator, for generating an analog representation signal of the encoded and modulated transmit signal;

a plurality of mapping functions that each select an effectively continuously valued control signal for at least one device within the transmitter apparatus in response to a desired average transmit power signal or a combination of a peak to average power ratio signal and a desired average transmit power signal, the plurality of mapping functions each comprising a table having a plurality of control signal values each with a corresponding desired transmit power value; and

at least one device within the transmitter having a plurality of control ports input, each control port input coupled to a multidimensional mapping function of the plurality of mapping functions such that at least one parameter of the transmitter apparatus is adjusted in response to at least one of the plurality of control signals.

18. (canceled)

19. (canceled)

20. (original) The apparatus of claim 17 wherein the said at least one device within the transmitter is a power amplifier, a stage or stages of a power amplifier, a drive amplifier, an

AGC amplifier, a power supply to a power amplifier and/or other devices in a transmitter, a mixer, a matching network, a filtering means, a power combining or coupling means, a charging means, a voltage or current generation or regulation means, or other means, or a combination of these.

21. (previously presented) The apparatus of claim 17 wherein the said at least one parameter includes a bias, a power supply voltage, a stage switch-in, a stage switch-out, a turning on, a turning off, a gain, a charging duty cycle, a conducting angle, an amplifier class change, a load, or an impedance.

22. (canceled)

23. (previously presented) The apparatus of claim 17, wherein said multidimensional mapping function includes an input variable associated with a transmitter temperature.

24. (previously presented) The apparatus of claim 17, wherein said multidimensional mapping function includes an input variable associated with a battery voltage.

25. (currently amended) A method for optimizing transmitter power efficiency in a transmitter apparatus, the method comprising:

generating an encoded and modulated signal from a digital input signal

converting the encoded and modulated signal into an analog transmit signal;

generating a desired average transmit power level value, the desired average transmit power level value being derived from an open loop power control signal and a closed loop power control signal; and

continuously mapping the desired average transmit power level value to a control signal value for at least one device within the transmitter apparatus to achieve an optimized transmitter power efficiency while still meeting out of band spurious emissions and waveform quality requirements.

26. (original) The method of claim 25, wherein said at least one device within the transmitter is a power amplifier.

27. (original) The method of claim 25, wherein said control signal is a power amplifier control

signal.

28. (original) The method of claim 25 and further including generating an automatic gain control amplifier control signal in response to the desired transmit power level value.

29. (canceled)

30. (currently amended) A method for optimizing transmitter power efficiency in a transmitter apparatus, the method comprising:

- generating an encoded and modulated signal from a digital input signal and also generating a data indicator signal corresponding to the encoded and modulated signal;

- converting the encoded and modulated signal into an analog transmit signal;

- selecting, in response to the data indicator signal, an output peak to average power ratio signal value from an array of peak to average power ratio signal values each having a corresponding data rate or data format;

- generating a desired average transmit power level signal value;

- summing the desired average transmit power level signal value and peak to average power ratio signal value to generate a peak transmit power level signal value; and

- continuously mapping the value of the peak transmit power level signal to a value of an at least one control signal for at least one device within said transmitter apparatus that controls at least one parameter within said transmitter apparatus to achieve an optimized power efficiency of the transmitter apparatus while still meeting out of band spurious emissions and waveform quality requirements.

31. (original) The method of claim 30 wherein said at least one device within said transmitter apparatus is a power amplifier.

32. (original) The method of claim 30, wherein said control signal is a power amplifier control signal.

33. (original) The method of claim 30 wherein the desired transmit power level is generated in response to an open loop power control signal and a closed loop power control signal.

34. (original) The method of claim 30 wherein the control signal is a digital signal and further

including converting the control signal to an analog signal prior to adjusting the at least one parameter of said at least one device within said transmitter apparatus.

35. (original) The method of claim 30 and further including low pass filtering the control signal.

36. (canceled)

37. (canceled)

38. (canceled)